



GREWIN INDUSTRIAL GROUP CO.,LTD.

TEL/WhatsApp: +86 18622096679

Mail: admin@coilwindingmachinechina.com

Web:www.coilwindingmachinechina.com



WhatsApp



WeChat

I. Overview

Instrument GW-901RH for coil turns is added with resistance measuring device on the basis of GW-901, it can not only conveniently measure the coil turns but also measure the coil resistance. The instrument does not need to replace the stroke when measuring the resistance fast and high efficiency. The shape and size of the coil have little influence on the measuring accuracy. From 0 to 60000 laps without range transformation can be accurately measured, thus improving the convenience of use and increase the life of the instrument.



II. Features

- The microprocessor controls all functions mathematically
- Simple operation, no range conversion automatic display of the number of turns or resistance measured
- With an accuracy of 0.2%
- 5-bit direct-reading digital display
- Good value for money
- Wide Availability
- Measuring the size of the sensor, can be customized according to user needs

GREWIN INDUSTRIAL GROUP CO.,LTD.

Add: The fourth floor A-A3 zone aviation business area,Dongli Distr,Tianjin,China.



GREWIN INDUSTRIAL GROUP CO.,LTD.

TEL/WhatsApp: +86 18622096679

Mail: admin@coilwindingmachinechina.com

Web:www.coilwindingmachinechina.com



WhatsApp



WeChat

III. Main Technical Index

SPECIFICATIONS				
Model	GW-901RH-10	GW-901RH-6	GW-901RH-4	GW-901RH-X
Inner diameter	$\Phi > 10\text{mm}$	$\Phi > 6\text{mm}$	$\Phi > 4\text{mm}$	Special Size: Inner < 4 mm, H > 110 mm. special size accuracy and range please refer to GW-901 Chart. CoilH > 110mm, outer > 120mm. separate type
Outside diameter	$\Phi < 120\text{mm}$			
Height	$H < 110\text{mm}$			
Sensor specification	$\Phi 10$	$\Phi 6$	$\Phi 4$	
Range	0~60000turns			
Accuracy	0~300 turns ± 0 turns 300~500 turns ± 1 turns 500~20000 turns $\pm 0.2\%$ turns 20000~60000 turns $\pm 0.5\%$ turns			
Speed	Fast 3/sec. Slow 1.2/Sec.			
Size	About 370×220×110 (mm)			
Weight	About 10 kgs			
Resistance measurement accuracy	$\pm 0.2\%$ (0.1 Ω ~100K Ω)			
Resistance measurement range	0.00001 Ω ~100K Ω			

GREWIN INDUSTRIAL GROUP CO.,LTD.

Add: The fourth floor A-A3 zone aviation business area,Dongli Distr,Tianjin,China.



GREWIN INDUSTRIAL GROUP CO.,LTD.

TEL/WhatsApp: +86 18622096679

Mail: admin@coilwindingmachinechina.com

Web:www.coilwindingmachinechina.com



WhatsApp

WeChat

GREWIN INDUSTRIAL GROUP CO.,LTD.

Add: The fourth floor A-A3 zone aviation business area,Dongli Distr,Tianjin,China.